


## Calypso Prime with DMX Protocol



### Benefits

- DMX ready; requires only a connection to an appropriate front end controller
- DMX512 protocol
- Heavy duty relays can be manually overridden

### Features

- Direct DMX connection via any controller that communicates on a RS485 network
- Control is added through a DMX controller
- Heavy duty latching relays
- Enclosure has a hinged door with a key lock

### Common Applications

- Commercial applications that have a DMX controller that communicates on a RS485 network
- Residential applications that have a Touch-Plate Master Controller or DMX controller that communicates on a RS485 network

### Specifications

#### Standards

- UL recognized system
- UL listed relays

#### Power

- Primary voltage is either 120VAC or 277VAC
- Secondary voltage is either 18VAC or 24VAC

#### Load Type

- Incandescent lighting
- Fluorescent lighting
- LED lighting
- Magnetic low-voltage lighting
- Electronic low-voltage lighting

#### Physical Design

- Enclosure: Nema 1; #16 U.S. Gauge Steel (Indoors Only)

#### Environment

- 0 - 60°C (0 - 140°F) non-condensing atmosphere

## How to Order the Calypso Prime with DMX Protocol

Part Number	Description	Dimensions
CPSPD-25120-08RP	Calypso Prime w/DMX, 25Amp Relays, 120VAC, 8 Relay Panel	21.5"L x 14.25"W x 3.75"D
CPSPD-25120-16RP	Calypso Prime w/DMX, 25Amp Relays, 120VAC, 16 Relay Panel	26"L x 14.25"W x 3.75"D
CPSPD-25120-24RP	Calypso Prime w/DMX, 25Amp Relays, 120VAC, 24 Relay Panel	34.25"L x 14.25"W x 3.75"D
CPSPD-25120-32RP	Calypso Prime w/DMX, 25Amp Relays, 120VAC, 32 Relay Panel	28"L x 24"W x 5"D
CPSPD-25120-40RP	Calypso Prime w/DMX, 25Amp Relays, 120VAC, 40 Relay Panel	28"L x 24"W x 5"D
CPSPD-25120-48RP	Calypso Prime w/DMX, 25Amp Relays, 120VAC, 48 Relay Panel	36"L x 24"W x 6"D
CPSPD-25277-08RP	Calypso Prime w/DMX, 25Amp Relays, 277VAC, 8 Relay Panel	21.5"L x 14.25"W x 3.75"D
CPSPD-25277-16RP	Calypso Prime w/DMX, 25Amp Relays, 277VAC, 16 Relay Panel	26"L x 14.25"W x 3.75"D
CPSPD-25277-24RP	Calypso Prime w/DMX, 25Amp Relays, 277VAC, 24 Relay Panel	34.25"L x 14.25"W x 3.75"D
CPSPD-25277-32RP	Calypso Prime w/DMX, 25Amp Relays, 277VAC, 32 Relay Panel	28"L x 24"W x 5"D
CPSPD-25277-40RP	Calypso Prime w/DMX, 25Amp Relays, 277VAC, 40 Relay Panel	28"L x 24"W x 5"D
CPSPD-25277-48RP	Calypso Prime w/DMX, 25Amp Relays, 277VAC, 48 Relay Panel	36"L x 24"W x 6"D
Contact the Factory for Ordering Assistance		

## Wiring Diagram

This wiring diagram does not show all the connections. Please see the Calypso Prime DMX manual for further wiring instructions.

